

WAC LIGHTING

Plug-In Electronic Transformer

120VAC/24VAC 60W

Model & Product
EN-2460-P-AR Plug-in Electronic Transformer with Open Splice 120V Input 24V Output 60 Watt

L x W x H
2.75IN x 1.625IN x 1.75IN

Fixture Type: _____
Catalog Number: _____
Project: _____
Location: _____

Example: **EN-2460-P-AR**

DESCRIPTION

Low Voltage plug-in Class 2 electronic transformer designed to be used as a plug-and-play style transformer. Contains an on/off toggle switch at the base and a 72" detachable cord with an open splice. Inherently protected and power limited, protecting the lighting system from both normal and abnormal short circuits. Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp. Ideal for WAC Lighting under cabinet systems.

FEATURES

- 1W minimum load
- UL listed Class 2 plug-in electronic transformers
- Plug-in power supply with on/off switch and 6' detachable cord
- Class 2 transformers are required for most cabinet listed fixtures
- Inherently protected and power limited, protecting the lighting system from both normal and abnormal short circuits.
- Built-in auto reset, soft start, short and overload circuit
- 5 year warranty

SPECIFICATIONS

Construction	Polycarbonate
Input:	120 VAC,50/60Hz
Finish:	Black
Standards:	UL, cUL, Dry Location Listed



FINISHES:



Black


WAC LIGHTING

Plug-In Electronic Transformer

120VAC/24VAC 60W

Fixture Type: _____
Catalog Number: _____
Project: _____
Location: _____

ACCESSORIES

	<i>Model</i>	<i>Description</i>	<i>Finish</i>
	MTB-01	Multiple Terminal Block	Black