

WAC LIGHTING

InvisiLED

120V/24V Plug-in Class 2 Transformer

Model & Max Output Power	Product	L x W x H
EN-24100-P-AR-T 100 EN-2460-P-AR-T 60	Plug-in Electronic Transformer for InvisiLED Tape Light 120V Input 24V Output 100 Watt Plug-in Electronic Transformer for InvisiLED Tape Light 120V Input 24V Output 60 Watt	2.75IN x 1.625IN x 1.75IN

Fixture Type: _____
Catalog Number: _____
Project: _____
Location: _____

Example: **EN-24100-P-AR-T**

DESCRIPTION

Low Voltage plug-in Class 2 electronic transformer designed to be used as a plug-and-play style transformer. Contains an on/off toggle switch at the base and a 72" detachable cord. Models that end in -T include a lead cable for InvisiLED Tape Light systems, and models that end in -S include a lead wire for Line and Straight Edge under cabinet lighting systems. Inherently protected and power limited, protecting the lighting system from both normal and abnormal short circuits. Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp.

FEATURES

- 1W minimum load
- UL listed Class 2 plug-in electronic transformers
- Plug-in power supply and 6' detachable cord
- Class 2 transformers are required for most cabinet listed fixtures
- Inherently protected and power limited, protecting the lighting system from both normal and abnormal short circuits.
- Built-in auto reset, soft start, short and overload circuit
- On/Off switch - only 60W version
- 5 year warranty

SPECIFICATIONS

Construction	Polycarbonate
Input:	120 VAC,50/60Hz
Finish:	Black
Standards:	UL, cUL, Dry Location Listed



FINISHES:



Black